

# JT-DPS6600

Signal generator and frequency counter



The JT-JDS6600 Signal generator and frequency meter can generate signals up to 60 MHz in different waveforms and offers an outstanding quality with its frequency counter. The control panel with its buttons is very intuitive. Further, the Menu can be displayed in German, English and French language.



## MAIN FEATURES

Display type	TFT color LCD
Display size	2,4 Inch
Connection	BCN Signal terminals
Features	2 channel Signal generator 1 channel frequencycounter
Size	194 x 178 x 69 mm
Items delivered	signal generator, 2x BNC signal terminals, power supply

## FURTHER SPECIFICATIONS

Signal waveforms	Lorentz pulse, pulse, half-wave, noise, exponential rise/ fall, CMOS, a. m. m.
Frequency range:	
sine	0 - 60 MHz
square, triangle	0 - 15 MHz
PWM, CMOS, TTL, arbitrary	0 - 6 MHz
Min. frequency resolution	0,01 $\mu$ Hz
Frequency accuracy	$\pm$ 20 ppm
Frequency stability	$\pm$ 1 ppm/ 3 hours
Load capability of the outputs	150 mA max.
Operation temperature	0 - 40 $^{\circ}$ C
Operation humidity	< 80 %

## FURTHER DETAILS

Article No.	JT-DPS6600
EAN:	4250236817811
Customs Tariff No.	85432000